

Originate Example

About

Simple examples to use the originate API command to initiate calls.

Originate Example 1

Courtesy of SwK:

Simplified originate usage template:

```
originate ALEG BLEG
```

The full template from the FreeSWITCH API command interpreter:

```
originate <call url> <exten>|&<application_name>(<app_args>) [<dialplan>] [<context>] [<cid_name>] [<cid_num>] [<timeout_sec>]
```

originate Example 1

```
originate {origination_caller_id_number=9005551212}sofia/default/whatever@wherever 19005551212 XML default  
CALLER_ID_NAME CALLER_ID_NUMBER
```

This will make a call out to `sip:whatever@wherever` with the Caller ID number set to 9005551212. After the A-leg supervises (is answered) it will send the call to the XML dialplan using `context=default` with the destination number of 19005551212 using the Caller ID name and number specified in the fields `CALLER_ID_NAME` and `CALLER_ID_NUMBER`.

Originate Example 2

originate Example 2

```
originate {origination_caller_id_number=9005551212}sofia/default/whatever@wherever &bridge  
({origination_caller_id_number=8001234567}sofia/profile/someother@destination.com)
```

This does the same thing as Example 1, but bypasses the dialplan and just sends the connected A-leg directly to the bridge app for B-leg.

Additional Settings

You can also get fancy if you want to set additional channel variables in the originate command line:

```
originate {origination_caller_id_number=12345,ignore_early_media=true,call_timeout=60,hangup_after_bridge=true}  
sofia/default....
```